

602 Series

1 Amp Power Controllers



Access control system power requirements are uniquely different from other systems. Unlike camera system power requirements, access control systems draw more current for locking hardware and during access control-related events. 75 – 85% of access control operating problems and technical support calls are due to power issues.* Access control systems require steady and clean (filtered) low-voltage DC current with surge suppression to protect printed circuit boards and connected devices from damage due to dirty power (transients and voltage spikes).

SDC power supplies have been developed specifically to help reduce power system issues and to support electric locks and access control requirements. Our hybrid design combines the efficiency of switching power supplies with the inductive load handling capability of linear power supplies in various 12/24 VDC current output capabilities and enclosure sizes. Filtering and output voltage regulation provide protection and ensure the longevity of all system components.

The high performance, heavy-duty circuitry is ideal for inductive loads and multi-door applications. With the addition of SDC programmable controllers or relay modules, the user-friendly modular designs ensure versatility, interface capability and easy installation of virtually any electric locking devices, access controls and related fire & life safety equipment.

* SDC technical support logs.



MODELS

602RF 1 Amp DC Power Controller With Cabinet

602RFA 1 Amp DC Power Controller With Large Cabinet

602RFL 1 Amp DC Power Controller Less Cabinet



STANDARD FEATURES

- Regulated and filtered linear DC power
- Class 2 output
- Field selectable dual voltage
- Fire/emergency release input
- Isolated battery charging circuit
- Low battery disconnect
- Input and output surge protection
- Visual status indicator (LED)
- Cabinet enclosures with pre-configured control module mounting holes*

* Applies to RF and RFA models only.



OPTIONAL FEATURES

- Fire/emergency release manual reset switch
- System on/off switches
- 6' power cord
- Key lock cover
- 230 VAC, 50/60 Hz input
- Choice of compatible door control modules



APPLICATIONS

FIRE/EMERGENCY RELEASE INPUT

A fire alarm input provides simultaneous release of all fail safe locks and door holders in case of an emergency. An optional manual reset switch following a fire/emergency release or power loss is available to meet code compliance. When the optional manual reset feature is required, should an AC power loss occur or the emergency release input be actuated, personnel must restore secondary output power manually at the power supply after the emergency release signal is reset and/or AC power is restored.

ISOLATED BATTERY CHARGING CIRCUIT

A separate charging output provides 13.5 or 27 volts to fully charge the batteries. The secondary output is always precisely maintained at 12 or 24VDC to protect locking devices and components from over voltage while the batteries are charging. The specified secondary output current is also maintained while batteries are charging. Derating of the secondary output current is not required when charging batteries.

LOW BATTERY DISCONNECT

Batteries are disconnected from the output circuit prior to deep discharge preventing battery destruction. Batteries are not included and should be ordered separately.*

DOOR CONTROL MODULES

Door control relay modules are available to meet virtually any application need. All wiring for lock hardware, access controls, remote controls and monitoring is terminated at one central location. Installation and troubleshooting is simplified. Modules may be factory installed or ordered separately for field installation as needed. Cabinet enclosures are pre-configured with mounting holes to accommodate door control modules. All modules are individually fused for protection of multiple station systems.

* See related products for backup batteries.

INPUT & OUTPUT SURGE PROTECTION

Input and output surge protection is built-in. The AC input voltage is circuit breaker protected and the outputs are PTC protected.

VISUAL STATUS INDICATOR (LED)

LED tri-color status indicators provide information regarding the AC input, DC output and battery backup status.

SYSTEM ON/OFF SWITCHES

Optional System On/Off switches are available both inside the cabinet enclosure or on the cabinet enclosure cover.

6' POWER CORD

An optional 6' power cord simplifies installations that do not require conduit where permitted by code.

KEY LOCK COVER


Optional key lock cover available where tamper-resistance is required.

INTERNATIONAL STANDARD INPUT

Additionally an alternative 230VAC international standard input is an available option.



CROSS REFERENCE



	602	631	632	634	636
DC Output Rating	1 Amp	1.5 Amp	2 Amp	4 Amp	6 Amp
Small Cabinet	602RF	631RF	632RF	-----	-----
Large Cabinet	602RFA	631RFA	632RFA	634RF	636RF
Less Cabinet	602RFL	631RFL	632RFL	-----	-----

[CLICK TO VIEW](#)

[CLICK TO VIEW](#)

[CLICK TO VIEW](#)

[CLICK TO VIEW](#)

SPECIFICATIONS

	602RF	602RFA	602RFL
Input	115 VAC 800 mA 50/60 Hz	115 VAC 800 mA 50/60 Hz	115 VAC 800 mA 50/60 Hz
Output	12/24 VDC 1 Amp	12/24 VDC 1 Amp	12/24 VDC 1 Amp
Battery Charger	13.5/27 VDC 250 mA	13.5/27 VDC 250 mA	13.5/27 VDC 250 mA
Cabinet	12" x 12" x 4" 20 Guage	16" x 14" x 6½" 16 Guage	-----
Weight	9 lbs	20 lbs	3 lbs

BACKUP BATTERY DISCHARGE TIME

Standby Power	12 VDC			
Battery	RB12V4	RB12V4	RB12V4	RB12V4
Battery Qty*	1	2	3	4
Current Load	Power BackupTime (Hours)			
250 mA	19.6	49.4	84.8	124.4
500 mA	7.8	19.5	33.5	49.2
750 mA	4.5	11.3	19.5	28.6
1 Amp	3.1	7.7	13.3	19.4

Standby Power	24 VDC**	
Battery	RB12V4	RB12V4
Battery Qty*	2	4
Current Load	Power Backup Time (Hours)	
250 mA	19.6	49.4
500 mA	7.8	19.5
750 mA	4.5	11.3
1 Amp	3.1	7.7

[CLICK TO VIEW](#)

DOOR CONTROL MODULE CAPACTIY***

Power Supply	602RF		602RFA	
Battery Qty*	0-2	3-4	0-2	3-4
FB4	2	2	2	2
12VR	1	1	1	1
UR-1	4	2	4	2
UR2-4	-----	-----	2	1
UR4-8	-----	-----	2	1
CR4	2	1	2	1
ACM-1	2	2	2	2
EMC	1	1	2	1

[CLICK TO VIEW](#)

* Battery quantity based on size of SDC's RB12V4 backup batteries.

** For 24 VDC standby power, minimum order of (2) batteries. Batteries must be ordered in pairs.

*** Total combined load of modules and access control hardware may not exceed power supply rating.

CERTIFICATIONS

- UL 294 Access Control System Units
- UL 603 Power Supplies for Use with Burglar-Alarm Systems
- ULC-S318 Power Supplies for Buglar Alarm Systems

HOW TO ORDER

FOLLOW STEPS FOR ORDERING

 Designates optional step

1 SPECIFY MODEL			
602RF 1 Amp DC Power Controller With Cabinet			
602RFA 1 Amp DC Power Controller With Large Cabinet			
602RFL 1 Amp DC Power Controller Less Cabinet			
2 SPECIFY OPTIONS		3 SPECIFY DOOR CONTROL MODULES	
XMR Fire/Emergency Release Manual Reset Switch		XUR-1 Microprocessor Controller, Two Relays	
XPS-1 Power On/Off Inside Cabinet Enclosure		XUR2-4* Microprocessor Controller, Four Relays	
XPS-1A Power On/Off On Cabinet Enclosure Cover		XUR4-8* Microprocessor Controller, Eight Relays	
XPC 6' Power Cord		XFB4 Multiple Fused Output Relay	
XKL Key Lock Cover		XCR4 Four Station Control Relay	
-220 230 VAC, 50/60 Hz		XACM-1 Six Station Input Control Relay	
		XEMC Exit Device Sequencer	
		X12VR Voltage Control Regulator, 12VDC	
<small>*UR2-4 and UR4-8 boards can only be accommodated in the RFA large cabinet enclosure.</small>			
STEP NUMBER:	1	2	3
ORDERING EXAMPLE:	602RF	XMR XPS-1 XPC XKL	XUR-1

RELATED PRODUCTS

BACKUP BATTERIES

SDC power supplies equipped with batteries provide continuous operation of access controls, locking devices and peripheral components during a power failure.

[CLICK TO VIEW](#)

- RB12V4** 12V/5Ah Battery
- RB12V4-2** 12V/5Ah Battery, Qty 2 Pack
- RB12V7** 12V/7Ah Battery
- RB12V7-2** 12V/7Ah Battery, Qty 2 Pack

