

IP Pro Controller board

**FEATURES**

- Controls one door directly, with multi-door expansion capabilities
- Password protected built-in web server or FREE downloadable 'Grid' software
- Two Ethernet Ports allow for interfacing with additional IP devices like cameras additional door controllers, etc.
- Entry & exit reader capability
- Supports industry standard proximity, smart card, and multi-technology readers (Wiegand output)
- Compliant with PoE+ standard
- Internet Explorer, Firefox and Google Chrome browser support
- 15,000 users (up to 2 credentials per user)
- Batch card enrollment
- 250 User groups/Time Zones/Door Groups
- Audit Trail – Up to 5,000 events may be exported as a .csv file from web server, unlimited events from PC software interface
- Anti-tailgating
- Door Status Monitoring Input
- Request-to-Exit (REX) Input
- Lock Relay Output

**SPECIFICATIONS**

IP Pro Controller/Door Station

<b>Voltage</b>	12 VDC Input
<b>Current Consumption</b>	250mA (max)
<b>Operating Temperature</b>	14°F – 122°F (Indoor use only)
<b>Dimensions</b>	5.375" x 3.5" x 0.875" board only 9.25" x 6.5" x 2.1875" w/ ABS plastic enclosure
<b>Weight</b>	1lb
<b>Relay Output Type</b>	Form C (SPDT) x 2

<b>Relay Contact Rating</b>	Main (Lock) – 5A @ 30VDC Auxiliary – 1A @ 30VDC
<b>Connections</b>	Digital Inputs: 4 dry contact inputs Ethernet: RJ45 RS-485 Terminal Bus Reader Power – 12VDC Reader Data – Wiegand (26bit to 37bit) Reader LED Control – Red & Green Two Solid State outputs (100mA max)

IP Pro Splitter


<b>Input Voltage</b>	44 - 57 VDC
<b>Input Power</b>	30W max
<b>Output Power</b>	24W max
<b>Output Current</b>	2A @ 12V
<b>Relay Output Type</b>	Form C (SPDT) x 2

IP Pro Injector


<b>PoE+ Output Pin Assignment and Polarity</b>	4/5 (+), 7/8 (-)
<b>Output Power Voltage</b>	55VDC
<b>User Port Power</b>	30Watts (Guaranteed)
<b>Input Power</b>	0.8A @ 100-240VAC

The IP Pro Line of IP-based Access Controllers allows expansion from one Standalone door up to a 100-door "Grid." The Choice is yours! **It's like having a local area network for your doors without all the headaches of an enterprise system.**






IP Pro Controller board



IP Pro Door Station Expansion board



IP Pro Controller enclosure



IP Pro Injector IP Pro Splitter





602RFx12VRxIPDC shown with optional batteries  
See batteries on page 2

IP Pro™ Components		LIST
<b>IPDCE</b>	<b>IP Pro Controller</b> , board plus enclosure	<b>898.00</b>
<b>IPI-30</b>	<b>IP Pro Injector</b> , 30W PoE+	<b>198.00</b>
<b>IPS-12</b>	<b>IP Pro Splitter</b> , 12VDC PoE+	<b>233.00</b>

IP Pro™ Door Station		LIST
<b>IPDSE</b>	<b>IP Pro Door Station Expansion</b> , board plus enclosure	<b>679.00</b>


IP Pro™ Kit		LIST
<b>IPPRO-SKE</b>	<b>IP Pro Starter Kit</b> , including Controller board, Splitter, Injector plus Controller enclosure	<b>1,298.00</b>
<b>IPPRO-SK</b>	<b>IP Pro Starter Kit</b> , including Controller board, Splitter, Injector	<b>1,209.00</b>
<b>602RFx12VRxIPDC</b>	<b>1 Amp</b> , class 2 output power, 12/24 VDC dual output, <b>IPDC</b> Controller board, 12" W x 12" H x 3.75" D box	<b>1,175.00</b>
<b>602RFx12VRxIPDS</b>	<b>1 Amp</b> , class 2 output power, 12/24 VDC dual output, <b>IPDS</b> Door Station board, 12" W x 12" H x 3.75" D box	<b>1,007.00</b>

# Install - Expand - Control






- Embedded software
- Browser Accessible
- 1 to 32 doors
- FREE Access Control Software
- Single PC Accessible
- 1 to 100 doors

**EMBEDDED**  
software managed  
via web browser



or Download **FREE**  
**SOFTWARE**  
for full Grid Access





**PLUS features include:**

- Intuitive & easy to use software; similar look & feel to the IP Pro™ web browser interface
- Free, single PC software for up to 100 doors
- Configure & manage all your IP Pro™ controllers from a single interface – No enterprise headaches
- Wizard & quick start buttons for common tasks
- Automated management reporting
- E-mail alert notifications
- Utilizes the scalability of Microsoft SQL server
- Save more energy the more doors you add



**PLUS Hardware** is used by the installer to set up controllers, doors and user profiles

- Enable & edit IPPro controllers
- Enable & edit door settings
- Create event filters
- Enable e-mail notifications

**PLUS Manage** is used by system administrators to facilitate database changes required on a day-to-day basis, and offers various reporting tools

- Create, view, & edit users
- Add access & holiday schedules
- Generate user & event reports



**PLUS Server** is used by system administrators to perform specialized tasks, such as database backups, firmware updates, importing/exporting users

- Perform manual or schedule automatic backups
- Import/Export Users
- Perform IPPro firmware updates




Live System events can be monitored from either module!

Prox Reader		LIST
<b>IPRW300</b>	<b>Wiegand Reader - PROX, Mullion Mount, HID compatible (125 kHz)</b> includes Black and White Cover	<b>202.00</b>
<b>IPRW500</b>	<b>Wiegand Reader - PROX, Single Gang Box or Surface Mount, HID compatible (125 kHz)</b> includes Black and White Cover	<b>232.00</b>



Wiegand Reader		LIST
<b>918W</b>	Indoor digital keypad, Wiegand output	<b>171.00</b>
<b>920PW</b>	Digital keypad with Prox Reader, Wiegand output	<b>417.00</b>
<b>923PW</b>	Digital keypad, narrow, with Prox Reader, Wiegand output	<b>507.00</b>
<b>925PW</b>	Digital keypad with Prox Reader, Wiegand output, and privacy shroud	<b>520.00</b>



Cards, Key FOBS and Tags		Distributor Discount Code <b>MV List</b>
<b>HID1326-25</b>	Proximity Card, HID compatible, 25 cards	<b>171.00</b>
<b>HID1326-100</b>	Proximity Card, HID compatible, 100 cards	<b>683.00</b>
<b>HID1346-10</b>	Proximity Key Fob, HID compatible, 10 key fobs	<b>140.00</b>
<b>HID1346-100</b>	Proximity Key Fob, HID compatible, 100 key fobs	<b>1,365.00</b>
<b>PTAG-10</b>	Proximity Disc Tag, HID compadible, 10 tags	<b>78.00</b>
<b>PTAG-25</b>	Proximity Disc Tag, HID compadible, 25 tags	<b>186.00</b>

